

PRODUCT INFORMATION SHEET

Universal digital meter FULL-SMART



Product description

Digital meter used for diagnostics and detection of faulty components of electrical installations. Thanks to the FULL-SMART technology, it is very easy to use, it can be used even by inexperienced users. Used in the automotive, electrical and installation industries.

Characteristics

- SMART technology - the meter recognizes the measured parameter itself and automatically adjusts the measurement range (AUTO RANGE) of direct and alternating voltage, continuity or resistance test;
- SELECT - switch functions for non-contact NCV / capacitance / frequency measurement;
- TRUE RMS measurement of alternating current and voltage - precise determination of the effective value of current for both sinusoidal and distorted waveforms;
- NCV enables non-contact detection of current in conductors;
- DATA HOLD allows you to store the currently measured value on the display;
- the multimeter enables the measurement of direct and alternating voltage up to 600 V, resistance up to 40 M Ω , capacity up to 4 mF, frequency up to 4 mHz, continuity test and 1.5 / 9 V battery test;
- has a large LCD screen with backlight, which allows displaying the result of 4000;
- built-in flashlight allows you to work at night and in the dark;
- rubber casing protects against mechanical damage;
- comfortable, ergonomic, compact shape enables comfortable work with one hand;
- powered by a 2x1.5 V AAA battery, increased battery life thanks to the automatic switch-off function;
- the set includes a test lead.

Technical data

AC voltage measurement: 0-600V DC
voltage measurement: 0-600V
Capacitance measurement: max. 4 mF
Resistance measurement: 40 M Ω
Frequency measurement: 4 mHz
Battery measurement: 1.5 / 9V

HT1E615	5902801365713	204 x 39 x 30 mm	1	

